

Ferrule OD and Crimp Dimensions

FF Part No	Outside Diameter (mm)	Crimp Diameter (mm)	Outside Diameter (mm)	Crimp Diameter (mm)
	Old 7000 Series	Old 7000 Series	New 8000 Series	New 8000 Series
SN103	19.0	15.4	18.0	14.4
SN104	20.0	15.8	19.0	15.0
SN105	22.0	17.9	21.0	17.3
SN106	24.0	19.6	23.0	18.7
SN108	28.5	24.5	27.5	22.8
SN110	32.0	27.6	31.0	26.6
SN112	36.0	31.1	35.0	30.3
SN116	43.0	38.0	43.0	38.1
SN120	52.0	46.4	51.0	45.8
SN124	58.0	53.5	58.0	52.8
SN203	21.0	16.6	20.0	16.2
SN204	22.0	17.6	21.0	16.8
SN205	24.0	19.5	23.0	19.0
SN206	25.5	21.0	25.0	20.1
SN208	30.0	25.1	28.0	23.4
SN210	34.0	29.2	32.0	27.4
SN212	38.0	33.0	36.0	31.2
SN216	46.0	40.5	45.0	39.5
SN220	56.0	50.0	56.0	48.4
SN224	64.0	56.5	64.0	56.0
SN703	14.0	11.7	14.0	11.7
SN704	17.0	14.0	17.0	13.9
SN705	19.0	16.5	19.0	16.2
SN706	21.0	18.7	21.0	18.0
SN708	25.5		25.5	21.9
SN710	28.5		28.5	25.7
SN712	32.0		32.0	27.9
SN716	40.0		40.0	36.1